## Huawei E1752 USB modem

# INŠTALÁCIA NA OS WIN, NASTAVENIE MOBILE PARTNER

1. inštalácia 2. pripojenie 3. vytvorenie profilu 4. voľba siete 5. merač dát 6. PIN, SMS centrum, diagnostika

### 1. inštalácia

Modem je samoinštalačný, po správnom zdetekovaní zariadenia sa Vám spustí inštalácia (v niektorých prípadoch je potrebné spustiť inštaláciu manuálne z nájdenej USB jednotky)



### 2. <u>Pripojenie – ikona Connection</u>

Po nainštalovaní sa zariadenie identifikuje voči OS ako modem a spustí sa hlavná aplikácia Mobile Partner. Modem je prednastavený na pripojenie, v profile je štandardne apn: **internet**. Kliknete **"connect"** 

🚟 Mobile Partner	
Ele Operation Iools Help	
Connection 🔤 Statistics 💽 Text 🔽 Phonebook	orange
Profile Name: Drange Internet Connect	
Till WCDMA Orange	

### 3. <u>Nastavenie profilu pre pripojenie</u>

### zvolíte Tools - Options

📻 Mobile Partner		
Eile Operation Tools Hel	p	
Connectio PIN Ope Choose Diagnos Optione	arations Device Device tics	orange
Profile Name:	Orange Internet	
WCDMA Orange	Ea	

🗎 General	Dial-Up		
Profile Management	Profile Name napíšeme názov profilu		New
C Network			<u>D</u> elete
	APN		<u>E</u> dit
	Dynamic	Static     St	<u>S</u> ave
	APN:	adresuþpn	Undo
	Authentication		
	Access number:	*99#	Set as Default
	User name:		Sec as pollogic
	Password:		
		<u>A</u> dvanced	

zvolíte Profile Management - New a vyplníte. Uložíte Save

# 4. Voľba siete

# zvolíte Tools - Options - Network

Options		×
<ul> <li>Ceneral</li> <li>Text Message</li> <li>Profile Management</li> <li>≥ Network</li> </ul>	Network Type Network Type WCDMA preferred GSM only GSM preferred WCDMA only WCDMA preferred	Apply
	ок	Cancel

General	Network Type Registration Mode
📄 Text Message	
Profile Management	Auto search and register
Network	Manual search and register

### 5. <u>Merač – ikona Statistics</u>

Resetujete cez kontextové menu (opačný click myšou) "Reset Statistics"

🚟 Mobile Partner			
Eile Operation Tools Help			
Connection 🛄 Statistics		Text 🗾 Phonebook	orange
	Speed (KB/s)	60.0 55.0 50.0 45.0 40.0 35.0 30.0 25.0 20.0 15.0 10.0 5.0 0.0 Upload Speed Download Speed	
III WCDMA Orange			

6. PIN, SMS centrum, diagnostika

### PIN

zvolíte Tools - PIN Operations

🚟 Mobile Partner	-		
<u>File</u> <u>O</u> peration	<u>T</u> ools <u>H</u> elp		
Connectio	<u>P</u> IN Operations → <u>C</u> hoose Device	<u>E</u> nable PIN Verification <u>D</u> isable PIN Verification	
🔷 Transfer	<u>D</u> iagnostics Options	Modify PIN	
Fransfer Tin ⊡ ⊡ ••• → Pupload	ne: 00:00:00	Unlock PIN	
Speed:	0.00 KB/s .00 KB	50.0	
Download	0.00 <i>K</i> B/c	45.0	

# SMS centrum zvolíte Tools – Options – Text Messages

Options			
<ul> <li>General</li> <li>Text Message</li> <li>Profile Management</li> <li>Network</li> </ul>	Text message handling Show a notification when Play a sound when a new Sound file name: C:\Program Files\Mobile Pa	a new text message arrives v text message arrives rtner\plugins\SMSUIPlugin\SN	15Voice, way
	SMSC Message Centre Number: Storage Period: Request delivery report	+421905303303 Maximum	
		ОК	Cancel

# Diagnostika zvolíte Tools – Diagnostics

Diagnostics	
Messages in SIM/USIM:	0 / 50
Contacts in SIM/USIM:	3 / 250
IMEI Number:	359638010010902
IMSI Number:	231019850042468
Firmware Version:	11.314.17.00.00
Hardware Version:	CD57TCPU
Model:	E169
Serial Number:	D42AB10831300211
Re	efresh Cancel